

Osaka/Felix/Zalo pendant

Thank you for purchasing this product. Please read the instructions and warnings carefully before use to ensure safe and satisfactory operation of this product.

Warnings.

- This is a double insulated product and does not require an earth.
- It is recommended that this fitting is installed by a qualified electrician.
- This fitting should be fitted in accordance with IEE Regulations and the Building Regulations.
- To prevent electrocution, switch off at the mains supply before installing or maintaining this fitting. Ensure other persons cannot restore the electricity supply without your knowledge.
- If you are in any doubt, please consult a qualified electrician.
- If replacing an existing fitting, make a note of the connections.
- Always use the correct type and wattage bulb. Never exceed the wattage stated.
- When changing a bulb, always switch off at the mains and allow the old bulb to cool down before handling. Dispose of used bulbs carefully.
- The bulb and surrounding parts can become extremely hot during use.

Instructions.

1. Ensure the house electricity supply is switched off at the fuse board.
2. If removing an existing fitting, note down all wiring connections.
3. Unscrew the ceiling cap anti-clockwise from the wind up mechanism.
4. Drill holes into the ceiling, appropriate for 6 mm rawl plugs (1).

Caution: Mind electric cables in the ceiling!
If there is any doubt, use an appropriate testing apparatus.

5. Mount the CABLE LIFT to the ceiling by using 3,5 x 5 mm screws (convex or flat heads)(2).
6. Connect the electrical wires by screwing them to the vacant side of the strip connector(3).
7. Ensure that no loose strands of wire are left out of the connections.
8. Gently tighten the brake screw (5) so that the lamp is held in position by its dead weight.
9. Put the ceiling cap on and screw it clockwise with gentle force.
10. Fit the bulb type/wattage as indicated on the luminaire.

The wattage indicated must not be exceeded.

11. Switch on the electricity supply at the fuse board.

Please retain this information leaflet for future reference.

